



**BUREAU
VERITAS**

Certificate of compliance

Applicant:

JIANGSU GOODWE POWER SUPPLY TECHNOLOGY CO., LTD
No.90 Zijin Rd., New District,
Suzhou, 215011
China

Product:

Grid-tied photovoltaic (PV) inverter

Model:

GW4K-DT
GW5K-DT
GW6K-DT
GW8K-DT
GW10KT-DT
GW12KT-DT
GW15KT-DT

Use in accordance with regulations:

Automatic disconnection device with three-phase mains surveillance in accordance with EN50549-1:2019 for photovoltaic systems with a three-phase parallel coupling via an inverter in the public mains supply. The automatic disconnection device is an integral part of the aforementioned inverter.

Applied rules and standards:

EN 50549-1:2019
Requirements for parallel connection of installations with distribution networks - Part 1: Connection to an LV distribution network - Production of installations up to and including Type B
EN 50438:2013
Requirements for micro-generating plants to be connected in parallel with public low-voltage distribution networks
DIN V VDE V 0126-1-1:2006 (4.1 Functional safety)
Automatic disconnection device between a generator and the public low-voltage grid

At the time of issue of this certificate the safety concept of an aforementioned representative product corresponds to the valid safety specifications for the specified use in accordance with regulations.

Report number:

ZEM-ESH-P19112903

Certification Program: NSOP-0032-DEU-ZE-V01

Certificate number:

U20-0206

Date of issue:

2020-03-31



Certification body Bureau Veritas Consumer Products Services Germany GmbH accredited to DIN EN ISO/IEC 17065
A partial representation of the certificate requires the written approval of Bureau Veritas Consumer Products Services Germany GmbH

Appendix

Extract from test report according to EN 50549-1

Nr. ZEM-ESH-P19112903

Type Approval and declaration of compliance with the requirements of EN 50549-1.

Manufacturer / applicant:
 JIANGSU GOODWE POWER SUPPLY TECHNOLOGY CO., LTD
 No.90 Zijin Rd., New District,
 Suzhou, 215011
 China

Micro-generator Type

Grid-tied photovoltaic inverter

	GW4K-DT	GW5K-DT	GW6K-DT	GW8K-DT
	180 - 850			
MPP DC voltage range [V]				
Input DC voltage range [V]	max. 1000	max. 1000	max. 1000	max. 1000
Input DC current [A]	12,5/12,5	12,5/12,5	12,5/12,5	12,5/12,5
Output AC voltage [V]	3/N/PE 400	3/N/PE 400	3/N/PE 400	3/N/PE 400
Output AC current [A]	6,4 * 3	8 * 3	9,6 * 3	12,8 * 3
Output power [W]	4000	5000	6000	8000
Output power [VA]	4400	5500	6600	8800

	GW10KT-DT	GW12KT-DT	GW15KT-DT
	180 - 850		
MPP DC voltage range [V]			
Input DC voltage range [V]	max. 1000	max. 1000	max. 1000
Input DC current [A]	12,5/12,5	12,5/25	12,5/25
Output AC voltage [V]	3/N/PE 400	3/N/PE 400	3/N/PE 400
Output AC current [A]	16 * 3	20,3 * 3	24 * 3
Output power [W]	10000	12000	15000
Output power [VA]	11000	14000	16500

Firmware version

V1.00.00.01

Measurement period:

2019-11-29 to 2020-03-10

Description of the structure of the power generation unit:

The power generation unit is equipped with a PV and line-side EMC filter. The power generation unit has no galvanic isolation between DC input and AC output. Output switch-off is performed with single-fault tolerance based on two series-connected relays in each line and neutral. This enables a safe disconnection of the power generation unit from the network in case of error.

Appendix

Extract from test report according to EN 50549-1

Nr. ZEM-ESH-P19112903

Setting of the interface protection:

Parameter	Max. disconnection time	Min. operate time	Trip value
Over voltage (stage 1) ^a	3s	-	230V +10% (253V)
Over voltage (stage 2)	0,2s	0,1s	230V +15% (264,5V)
Under voltage	1,5s	1,2s	230V -15% (195,5V)
Over frequency	0,5s	0,3s	50Hz +4% (52Hz)
Under frequency	0,5s	0,3s	50Hz -5% (47,5Hz)
Reconnection settings for voltage (normal operational startup)	0,85V _n (195,5V) ≤ V ≤ 1,10V _n (253V)		
Reconnection settings for frequency (normal operational startup)	49,5Hz ≤ f ≤ 50,1Hz		
Reconnection time (normal operational startup)	≥ 60 s		
Reconnection settings for voltage (automatic reconnection after tripping)	0,85V _n (195,5V) ≤ V ≤ 1,10V _n (253V)		
Reconnection settings for frequency (automatic reconnection after tripping)	49,5Hz ≤ f ≤ 50,1Hz		
Reconnection time (automatic reconnection after tripping)	≥ 60 s		
Active power gradient after reconnection	10% P _{Emax} / per minute		
Active power delivery at under frequency	electronic inverter, no active power reduction		
Power response to over frequency (frequency / droop s)	50,2Hz / 5%		
Permanent DC-injection	0,5% of rated inverter output current or 20mA		
Rate of change of frequency (ROCOF)	2Hz/s		
Loss of mains according EN 62116 (LoM)	2,0s		

Note:

^a Over voltage – stage1: 10 min-mean-value corresponding to EN 50160. Default interface setting according to EN 50438:2013 are used.

The settings of the interface protection are password protected adjustable.

In case the above stated generators are used with an external protection device, the protection settings of the inverters are to be adjusted according to the manufacturer's declaration.

The above stated generators are tested according to the requirements in the EN 50549-1:2019. Any modification that affects the stated tests must be named by the manufacturer/supplier of the product to ensure that the product meets all requirements of the EN 50549-1:2019.